

Electrical Characteristics

Type	Wattage (Watts)	Primary Amps.	Min. Power Factor	Min. Efficiency (%)	Secondary Full Load Amperes	Secondary Short Circuited Amperes	Load Ohms	Secondary Max Open Circuit Voltage – RMS	Bildal Catalogue No. Without Earthing
L-831-1	30/45	6.6	0.95	80	6.53 – 6.67	6.6 – 7.1	1.15	25	BE045665
L-831-2	30/45	20.0	0.95	80	6.53 – 6.67	6.6 – 7.1	1.15	25	BE045204
L-831-3	65	6.6	0.95	80	6.53 – 6.67	6.6 – 7.1	1.60	30	BE0656621
L-831-4	100	6.6	0.95	85	6.53 – 6.67	6.6 – 7.1	2.44	70	BE100667
L-831-5	100	20.0	0.95	85	6.53 – 6.67	6.6 – 7.1	2.44	70	BE100668
L-831-6	200	6.6	0.95	90	6.53 – 6.67	6.6 – 7.1	4.82	100	BE2006612
L-831-7	200	20.0	0.95	90	6.53 – 6.67	6.6 – 7.1	4.82	100	BE2002013
L-831-10	300	6.6	0.95	90	6.53 – 6.67	6.6 – 7.1	8.25	135	BE3006614
L-831-11	300	20.0	0.95	90	6.53 – 6.67	6.6 – 7.1	8.25	135	BE3002015
L-831-16	10/15	6.6	0.95	70	6.53 – 6.67	6.6 – 7.1	0.34	8.0	BE015661
L-831-17	20/25	6.6	0.95	70	6.53 – 6.67	6.6 – 7.1	0.57	8.0	BE0256622
L-831-18	150	6.6	0.95	85	6.53 – 6.67	6.6 – 7.1	3.58	70	BE150669
L-831-19	150	20.0	0.95	85	6.53 – 6.67	6.6 – 7.1	3.58	70	BE1502010
305A/143	45	8.3	0.95	85	6.53 – 6.67	6.6 – 6.95	1.15	13.6	BE045833
305A/142	65	8.3	0.95	85	6.53 – 6.67	6.6 – 6.95	1.60	19.6	BE065836
305A/141	200	8.3	0.95	90	6.53 – 6.67	6.6 – 6.95	4.82	60.8	BE2008311
	15/20	6.6	0.95	70	6.53 – 6.67	6.6 – 7.1	0.34	8.0	BE015202